

RT22 Hand transmitter

ON/OFF | UP/STOP/DOWN



The RT22 hand transmitter can control 24 Easywave receivers.

The RT22 has four levels (I to IV), each with six individually coded radio channels:

- 5 channels have the ON/OFF function
- 1 channel has the UP/STOP/DOWN function.

The multi-channel transmitter is best used when multiple Easywave receivers need to be controlled from a single hand transmitter.

Its solid housing and large buttons, which are easy to operate, make the RT22 suitable for industrial applications.



RT22E5022-01-23K

Technical specifications

Coding	Easywave
Frequency	868.30 MHz
Channels	24
Range	typically 150 m in good free-field conditions
Power supply	2x 3V-batteries, CR2032
Operating indicator	LEDs
Operation	see operating manual
Operating temperature	-20 °C to +60 °C
Dimensions (W/L/H)	60/150/22 mm
Weight	100 g (including batteries)
Color	anthracite similar RAL 7016

Scope of delivery

- Hand transmitter incl. batteries
- Operating manual

Models

Product number	Description
RT22E5022-01-23K	Hand transmitter, Easywave, 20x ON/OFF + 4x UP/STOP/DOWN, anthracite